

IRE12 IR REMOTE EXTENDER

RF
Frequency



Model: IRE12

Order Code: 37169700

Warranty: 12 months




The Pro2 IRE12 transmitter takes the standard IR signal from your existing remote controls and converts it to the more powerful and reliable RF frequency. The wireless receiver then converts those RF signals back to IR and allows you to control your equipment behind cabinets, even in another room!



In the box

- 1x Transmitter
- 1x Receiver
- 2x 9V power supply
- 3-way IR beamer
- User manual



Spare transmitter



- Spare transmitter (IRE12SPT) also available

Features

- IR Remote control Extender via UHF
- Control any audio/video equipment through walls
- Carrier Frequency: 433.92MHz
- Maximum range: 50 m line-of-sight
- Supports multiple IR Transmitter units

Specifications

Transmitter Unit	IR Frequency Input:	35~41kHz
	IR Receiving Range:	= 8m
	UHF Carrier Frequency:	433.92MHz
Receiver Unit	Power Requirements:	9VDC / 600mA
	UHF Carrier Frequency:	433.92MHz
	IR Frequency Output:	37 ± 1kHz
	IR Emitter Range:	= 3m
	Power Requirements:	9VDC / 600mA

